



# FISKE BROTHERS REFINING COMPANY

NEWARK, NEW JERSEY 07105 • TOLEDO, OHIO 43605

## CLEANING PROCEDURES FOR CHARGING MACHINES WHERE FISKE'S HP-76 IS TO BE USED

**HP-76** is a synthetic type transparent soluble oil when mixed with water to the proper proportion. Being a synthetic material, it is most important that the machine be cleaned as thoroughly as possible to obtain optimum results.

### **Directions:**

Before charging machine with Fiske HP-76, drain the machine completely, being sure to empty lines and hoses.

Remove all litter, then flush the machine for approximately 10 minutes with an alkali solution or a good commercial cleaner.

Drain the dirty solution from the machine, again being sure to empty lines and hoses.

Flush the entire machine system with clean water. Drain thoroughly.

Then add HP-76 to the machine and let the machine do the mixing. Should you run into an unusually hard water situation which may be the case in various parts of the country, it might be necessary to soften the water. This can be achieved by adding approximately ½ ounce to 1 ounce of trisodium phosphate or borax to each 50 gallons of solution.